

0vrC 快速配置手册

"请保存好设备说明书,以便查找设备激活码"

登陆 app.ovrc.com, 账号 support@dvaco.com。

OVIC	
Email	
Email	
Password	
Password	
Remember Me	
Create a New Account Forgot Password?	Log In

登陆账号后,可以查看账号内已经添加的 OVRC HUB 信息。点击 Add 添加

0	fC	OVIC	WHAT'S NEW Sept 2017 OvrC	Release - New	OvrC P	ro Enhanceme	ents & Parenta	I Controls BET	A Dismiss	Learn More	Ovrc Dvac	o v
	C Search	FIRMWARE	ATTENTION	华歌北京 北京		PRO 🕐				0 OvrC Home 10 Total D	Users evices NOTE	S DELET
—	+	tês Ø	6 🔛		SITE Q, S	SETTINGS (CLIENT SERVICE	S ENABLE C	VRC PRO	ALL CO	NNECTED DI	SCONNECTEI
3		9			NOTIFY	DEVICE V		IP ADDRESS	MANUFACTURER	UPDATE	CONNECT F	REBOOT
				्रि	*	100系列AP		192.168.1.179	Araknis Networks		Ð	ц
				(î)		办公区AP1		192.168.3.4	Araknis Networks		21 days discor	nected
		+ Add Cust	tomer			TALÌ]]		192.168.6.109	Araknis Networks	**	\rightarrow	<u>ت</u>
									Araknie Networke			uls *

弹出页面,填写用户信息,填写完成点击 Save



添加完成后在用户列表内出现新建用户

0	IC .	Ovrc Dvaco owner
<u>.</u>	Q. Search Customers ALL PRO FIRMWARE ATTENTION P3 PA PA PA	内蒙古通辺钻石郡7-3-2 内蒙古通辽 / PRO の Distal Devices DeLete Distal Devices DeLete
ER Ø	 ▲ 内蒙古通辽社石部7-3-2[®] ※ ▲ 华歌北京总部[®] ▲ 伊歌北京总部[®] ▲ 伊歌北京総部[®] ▲ 伊歌北京北京総部[®] ▲ 伊弥北京総部[®] ▲ 伊歌北京総部[®] ▲ 伊歌北京総部[®] ▲ 伊歌北京総部[®] ▲ 伊歌北京総部[®] ▲ 伊歌北京総部[®] ▲ 伊歌北京都 ▲ 伊歌北京都和北京都 ▲ 伊歌北京都和北京都 ▲ 伊歌北京都和北京都 ▲ 伊歌北京都和北京都 ▲ 伊歌北京都和北京都 ▲ 伊爾和北京都和北京都 ▲ 伊爾和北京都和北京都 ▲ 伊爾和北京都和北京都 ▲ 伊爾和北京都 ▲ 伊爾和北京都和北京都 ▲ 伊爾和北京都和北京都 ▲ 伊和北京都和北京都 ▲ 伊和和北京都和北京都 ▲ 伊和和北京都和北京都和北京都和北京都 ▲ 伊爾和北京都和北京都 ▲ 伊爾和北京都和北京都 ▲ 伊爾和北京都和北京都 ▲ 伊爾和北京都和北京都 ▲ 伊爾和北京都和北京都和和北京都和北京都和北京都和北京都和北京都和北京都和和北京都和	DEVICE Ste settings CLIENT SERVICES ENABLE OVRC PRO
		No Devices Start controlling and monitoring your devices remotely by adding them into your account. Add Device
	+ Add Customer	

点击 Add,添加 OVRC-HUB 的 MAC 地址,点击 Find。

Add Device		×
Customer 内蒙古-通辽钻石郡7-3-2	Location 内蒙古通辽	OVRC MAC 地址
Please enter the MAC address of an ins	talled device	\sim
ex: 95:16:AB:1C:2D:43		Find
Supporting o	The second secon	C LUMA
WIE		
		Close

搜索到设备,点击进入

Add Device	×
OvrC Pro Required	×
Enable OvrC Pro at this location to add this device.	
Cancel Enable OvrC	Pro



跳转至下图,此处填设备激活码,填入后点击 Activate 激活



激活码在说明书左上角,请保存好设备说明书,以便查找设备激活码。





DASHBOARD DEVICES SITE SETTINGS CLIENT SERVICES 信息显示 设置 服务 设备 0 0 0 ----ONLINE DEVICES OFFLINE DEVICES FIRMWARE UPDATES Internet Araknis Wired Araknis Wireless Add an OvrC Hub to run speed tests for this location remotely (included with OvrC Pro license) Add an OvrC Hub to view the LAN Map and Ping Responses for devices at this location remotely. Add Araknis access points at the location to remotely configure settings

OVRC-HUB 添加成功后页面跳转至 OVRC 系统页面



DASHBOARD	DEVICES	SITE SETTINGS	CLIENT SERVICES			
+ DEVICE	Search			ALL	CONNECTED	DISCONNECTED
			No Devices			
	Start control	lling and monitori	ng your devices remotely Add Device	by adding them inte	o your accoun	t.

弹出页面,输入 OVRC-MAC 地址,点击 Find。

Add Device		×
Customer 内蒙古-通辽钻石郡7-3-2	Location 内蒙古通辽	OVRC MAC 地址
Please enter the MAC address of an ins	stalled device	$\overline{\mathcal{V}}$
ex: 95:16:AB:1C:2D:43		Find
Supporting o	Ver 100 models from these brar	
WT		
		Close



弹出,填写设备的 serial number 号,点击 Submit

Add Device	×
Customer 内蒙古-通辽钻石郡7-3-2	Location 内蒙古通辽
OVRC-100-HUB	✓
Please enter the serial number of your O	C Hub. The serial number can be found on the device.
植宅设久	Submit
实与设备 serial 号	Close

弹出,输入设备自定义名称,方便记忆,点击 Save

Add Device		×
Customer 内蒙古-通辽钻石郡7-3-2	Location 内蒙古通辽	
OVRC-100-HUB		~
Name the device. Then add any additional in	fo about the device.	
Device Notes 填写自定 名称	X	
	Clo	ise Save

弹出页面,显示现在网络内有的支持 OVRC 功能的设备类型列表

Customer 内蒙古-道	重辽钻石郡7-3-2	Location 内蒙古通辽	
🕑 1 De	evice Added		
Your device	was added successfully, here are add	litional ones at that location.	
8	Networking Devices	网络设备	+
1	Surveillance Devices	监控设备	+
0	Audio Devices	音频设备	+



选择设备类型,弹出设备详细信息

Add Un	claimed Networking Device	S	×
	AN-300-RT-4L2W		
	AN-310-SW-24-POE		
	AN-500-AP-I-AC		
□	AN-500-AP-I-AC		
	AN FOO AD LAC		-
		Close	Save

勾选要添加进系统的设备,并命名,点击 Save

Add Unclaimed Networking Devic	ces 🛛 🗙
✓ ↔ AN-300-RT-4L2W	araknis路由器
AN-310-SW-24-POE	araknis-24口POE交换机
✓ AN-500-AP-I-AC	B1层AP健身房
✓ AN-500-AP-I-AC	1层AP大厅
AN 500 AD LAC	Close Save

重复上步,将所有需要的设备添加到系统

Add Ur	nclaimed Devices		×
Customer 内蒙古-ù	重辽钻石郡7-3-2	Location 内蒙古通辽	·
🥑 8 De	evices Added		
We found t	ne following unclaimed devices at this locat	tion.	
1	Surveillance Devices		+
0	Audio Devices		+
0	Control System Devices		+
			Close



添加完成后,自动返回"DEVICES 设备"列表页面。UPDATE: 有设备固件更新, CONNECT: Web 登陆设备, REBOOT: 重启设备。

DASHBO	ARD	DEVICES SITE SETTINGS	CLIENT SERVICE	ES				
+ DEVICE	Q Se	earch	C		ALL CO	INECTED	DISCONNEC	TED
STATUS	NOTIFY	DEVICE	IP ADDRESS		UPDATE	CONNECT	REBOOT	
③		araknis路由器	192.168.1.1	Araknis Networks	**	\rightarrow	也	5
ি		B1层AP健身房	192.168.1.20	Araknis Networks	**	⇒	ப்	>
		1层AP大厅	192.168.1.21	Araknis Networks	6 3	₽	ம்	×
(îr		三层东AP	192.168.1.22	Araknis Networks	**	₽	ц	>
ি		三层西AP	192.168.1.23	Araknis Networks	<u>63</u>	₽	ம்	×
		二层AP	192.168.1.24	Araknis Networks	**	₽	也	3

如果需要升级固件,点击对应设备的 UPDATE 按键,更新设备固件,弹出提示框,点击 Update Firmware





弹出固件的具体信息,点击 Continue 继续

Firmware Update	×
Current Firmware Version	*
VERSION DATE SIZE 3.0.4.151204 December 04, 2015 13.83 MB	
New Firmware Version	-
VERSION DATE SIZE 3.0.4.170324 June 01, 2017 14.70 MB	
Notes : URGENT Luma DVR Firmware Update This update improves the security of your recorder as well as compatibility with control systems, particularly Savant.	
If you do not update your firmware and change your admin password from its default, you are at risk for cyberattacks.	
Luma DVRs purchased after July will have this firmware.	+
Cancel	

设备提示信息

®		LUMA-500-DVR-8CH	192.168.1.40	Luma	Update in progress
更新完成	成后,	显示			

LUMA-500-DVR-8CH 192.168.1.40 Luma Description Luma Description D



设备列表内显示所有连接到网络设备

()	4/4:	Unspecified	192.168.1.11	Core Brands	2
•	-11/4-	Unspecified	192.168.1.12	Core Brands	×
(ł)	-1/4-	Unspecified	192.168.1.31	Core Brands	5
()	alfe-	Marantz-SR7010	192.168.1.49	D&M Holdings	5
()	alle-	Unspecified	192.168.1.10	Digiboard	2
()	4/4-	Unspecified	192.168.1.159	Guangdong Oppo Mob.	>
•	4/4-	Unspecified	192.168.1.135	Huawei Technologies	3
•	4/4-	MUSICSTREAM	192,168,1,30	ProMax Systems	Ş.
@ ;	4/4-	OpenWrt	192.168.1.129	Shenzhen Kaiboer Tec	5
()	-4/4-	USER-20170731LD	192.168.1.158	Wistron InfoComm(Ku	8.

点击设备进入,显示详情。点击 MORE,点击 INFO

customers > 内蒙古通辽钻石郡7-3-2 > 内蒙古通辽 > Unspecified						
DETAILS				INFO		
Device Status			_	HIDE		
Ø 55m 42s ONLINE SYSTEM UPTIN	3 1 ms ME LATENCY			CREFRESH		
General Information						
DEVICE NAME	Unspecified	IP ADDRESS	192.168.1.101			
MANUFACTURER	Core Brands	MAC ADDRESS				
HUB FIRST SEEN	1 hr	HUB LAST SEEN	2 mins			



弹出页面,添加设备名称,方便记忆查找。打开设备提醒

More Information	填写自定义	L	×
Device Name	名称		
G10			
Device Notifications () Receive notifications when thi	s device connects or a	disconnects from the net	work
Device Information	当设备」	二线/离线通过	过网络提醒
MAC Address			
LAN IP: 192.168.1.101			
Vendor: Core Brands			
First Soon: Sontombor 28 201	7 11 38 AM		
	Hide Device	Cancel	Save

重复以上步骤,将需要上线/离线通过网络提醒的设备都命名

@		ELAN G10	192.168.1.11	Core Brands		
٠		ELAN G1	192.168.1.12	Core Brands		
\$		NILES 6430	192.168.1.31	Core Brands		>
٠		Unspecified	192.168.1.101	Core Brands		
٠		影院功放	192.168.1.49	D&M Holdings		
@		灯控路畅网关 DS65L	192.168.1.10	Digiboard	$\overline{}$	
@	-	Unspecified	192.168.1.146	Guangdong Oppo Mob		

添加完成后,在"DASHBOARD 信息显示"页面可以查看设备的在线/离线情况





点击 Speed Test 可以测试网速

Speed Test 自动测速	×
Auto-Test Interval I	24 Hours 🗸
	Disabled
	8 Hours 24 Hours
Run Test	LOCATION 内蒙古通辽

点击 Run Test 开始测试网络



设备信息页面内可以查看现在链接到网络的设备获得的 IP 地址

tatus 📀 🤝	Device 🗸	Manufacturer	MAC Address	IP Address / Reservation 🕄 🦷
	HUAWEI_P9	Huawei Technologies	ACTO VOID AND	192.168.1.198 🔒
0	Honor_8	Huawei Technologies		192.168.1.161 🔒
	android-99b1e47c816cb1db	Guangdong Oppo Mobile Telecom		192.168.1.160 🔓
0	Unspecified	Guangdong Oppo Mobile Telecom	421034-0-0803	192.168.1.159 🔒
•	USER-20170731LD	Wistron InfoComm(Kunshan)Co.		192.168.1.158 🔒
0	android-b2f094c743b8fc76	Fn-link Technology Limited	1000 00100 0010	192.168.1.157 🔒
	new-host1	Rosemount		192.168.1.156 🔒
	android-37408802f1b5d26f	Guangdong Oppo Mobile Telecom	0.00110-00100-00100	192.168.1.155 🔒
0	HUAWEI_P9	Huawei Technologies	10054-0030312121	192.168.1.154 🔒
•	araknis-24囗POE交换机	Araknis Networks		192.168.1.153 🔒

设备信息页面内可以查看现在链接到网络的设备连接的信号强度

Status 🕦	Access Point	Device Operating System	Network ID Channel	MAC Address Manufacturer	Tx 🛛 🔻	Rx 🕄 🔍
? 100%	B1层AP健身房	iPhone	7-3-2 5GHz	40-40-10-70 Appe	0.9MB	0.5MB
? 13%	B1层AP健身房	bogon	7-3-2 2.4GHz	Huawe Technologies	0.4MB	0.5MB
? 97%	1层AP大厅	Unspecified	7-3-2 2.4GHz	Guangdong Oppo Mobil	0.3MB	0.1MB
? 40%	1层AP大厅	Unspecified	7-3-2 2.4GHz	Huawe Technologies	0.1MB	0.2MB
7%	二层AP	Unspecified	7-3-2 2.4GHz	Guangdong Oppo Mobil	0.0MB	0.0MB
22%	1层AP大厅	bogon	7-3-2 2.4GHz	Humo Technologies	0.0MB	0.0MB
? 4%	四层西AP	android-37408802f1b	7-3-2 2.4GHz	Guangdong Oppo Mobil	0.0MB	0.0MB
? 10%	四层西AP	android-1d7d1eeaec9_	7-3-2 2.4GHz	vivo Mobile Communic	0.0MB	0.0MB
? 4%	二层AP	android-37408802f1b	7-3-2 2.4GHz	Guangoong Oppo Mobil	0.0MB	0.0MB



在"SITE SETTINGS 设置"内有 OVRC 的基本设置和 OVRC-HUB 设置

General Settings / 基本设置		
Wireless Setup Configure wireless network settings for multiple access points	无线设置	
Content Filtering & Network Security Settings Configure network security settings and web content filtering po	BETA 内容过滤	悲和网络安全设置
OvrC Hub Settings		
Network Scan Frequency Configure how often the OvrC Hub scans the network.	扫描设备时间周期	1 Hour
Network Ports Scanned Configure the network ports that the OvrC Hub scans	扫描的端口	
Network VLANs Scanned Configure the VLANs that the OvrC Hub scans	VLAN 设置	
Speed Test Frequency Configure how often the OvrC Hub runs a network speed to	网速测试周期	24 Hours 🗸

点击进入 Wireless Setup,可以统一设置所有无线设备的无线名称和加密方式(支持 3 种: OPEN; WPA2-PSK; WPA2-PSK MIXED)。

填写完配置信息,选择对应的无线 AP,点击 Save,上传配置至无线 AP。

E asy Wireless Setup Customer: 内蒙古-通辽钻石郡7-3-2 Location	内蒙古通辽				
Create the primary wireless network on each a manage additional settings and guest network	cess point selected below. Please refer to the device configuration on each access point to s. Do not use this feature if there are VLANs configured on the Access Points below.)			
Wireless Network Name (SSID)	于线名称				
Security Type	加密方式				
WPA2-PSK	<u>×</u> _				
Security Passphrase	无线连接密码				
Apply to:					
✓ ? 1层AP大厅 192.168.1.21					
□					
□ 중 三层东AP 192.168.1.22					
□ ○ 三层西AP 192.168.1.23					
□ 示 二层AP 192.168.1.24					
□ ○ 四层西AP 192.168.1.25					
	Cancel Sa	ve			



在 "CLIENT SERVICES 服务"内可以添加/修改网络控制功能。



点击 Add,添加控制功能。填写控制功能的名称,选择功能的图标,选择被控设备,选择控制功能,如果控制多台设备点击添加(最多再添加4个设备),选择控制功能的使用时间间隔,点击 Save,生成控制按键。

	Command Name / Icon: 1层AP-REBOOT Location: 内蒙古通辽	
		图标
	被控设备	
	Select a device you want to control.	
	Reset the device: 被控设备支持的 Reset Device 控制功能	
添加其他设备	Add Another Device Limit: 5 devices 控制功能的使用	
	Choose how long the command should be disabled after running 间隔 This will give the affected device(s) time to reset. A MINUTE 2 MINUTES 3 MINUTES 5 MINUTES 10 MINUTES 10 MINUTES	
	Cancel Save	



点击功能图标启动功能。

DASHBO	DARD	DEVICES	SITE SETTI	NGS	CLIENT SERVICE	ES		
Client Services Commands 将功								能同步到
СОММА	NDS	NETWORK (CONTROLS	USERS	ACTIVITY		0'	vrC APP
Action	Comm	ands			Enable in OvrC	Home	01	
SORT	RUN	COMMAND				EDIT	DELETE	
1		1层AP-RE	BOOT			/	6	
Add Co	mmand							